

Anthony Downlight Optic Medium


Designed by Antonio Citterio, 2017



High-performance embedded light fixture for LED light source. Remote 220-240V power supply not included.

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)



Main specifications

Mounting	Ceiling recessed
Environment	Indoor dry location
LED type	Power LED
Lamp category	LED
Ilcos	No
Number of heads	1
Power (W)	10.26
Source flux (lm)	936
System flux (lm)	827

Physical

Colour	White
Trim	No
Orientation	Adjustable
Rotation (°)	360
Longitudinal tilting (°)	40
Recessed depth (mm)	90
Net weight (kg)	1.07
IP	20
IP external	20

Download

Mounting instructions [↓ PDF](#)

Photometric Files

LDT / IES [↓ ZIP](#)


Technical Drawings

2D [↓ ZIP](#)

3D [↓ ZIP](#)



Schematic light drawing



Photometric

Light distribution	Symmetric
CCT (K)	2700
CRI>	90
Beam angle C0-180 (°)	22
Beam angle C90-270 (°)	22

Electrical

Insulation class	III
Frequency (Hz)	50/60
Main voltage (Vac)	11.40
Driver	Remote excluded
Dimmable	Yes
Dimming type	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming
Emergency type	No

Notes

Standard trim cove in white for all finishes; black finish available under request. To obtain flood optics (35°) order Anthony Downlight Medium + flood lens.

Accessories & Power Supply



OPTIONAL
Accessory

Optical

08.0050.00

Flood lens



OPTIONAL
Accessory

Optical

08.8418.68A

Elliptical lens



OPTIONAL
Accessory

Optical

08.8419.14A

Honeycomb



OPTIONAL
Power supply

60.8530

Continuous current power supply of 25-50W, 110/240V - 50/60Hz with power current selected through adjustable 350mA - 25W /500mA - 35W/ 700mA - 50W /750mA - 54W /900/ 1050 mA - 60W switch. Dali 2, 0/1-10V or push dimming



OPTIONAL
Power supply

60.9188

Continuous current power supply of 13-20W, 110/240V - 50/60Hz with power current selected through adjustable 300 mA - 15W / 350 mA - 18W / 400/ 450/ 500/ 550/ 600/ 650/ 700/ 750/ 800/ 850/ 900 mA - 15W. switch. 0/1-10V or push dimming



OPTIONAL
Power supply

60.9233

Non dimmable continuous current power supply of 110/240V 32W, with power current selected through adjustable 350 mA-17W /500 mA-24W /700 mA-32W /900 mA - 32W switch



OPTIONAL
Power supply

60.9207

Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W /750 /800 /900 /1000 /1050mA - 38W



OPTIONAL
Power supply

60.9186

Continuous current supply source of 240V - 50/60Hz with dimmable Dali 2, push dimming. 300mA - 16W / 350mA - 18W / 400mA - 21W / 500mA - 27W / 600mA - 32W / 650 mA - 35W / 700 / 750 / 800 / 900 / 1000 / 1050 mA - 36W



OPTIONAL Power supply

60.9467

Continuous current power
supply, Mains dimming (AC
phase-cut dimming), leading &
trailing edge 220/240V - 50/60Hz,
250mA - 12W / 300mA - 14W /
350mA - 17W / 400mA - 19W /
450 / 500 / 600 / 650 / 700 /
750 / 800 / 850 / 900mA - 20W