





LEDS C R ST 927

13611 9200 ANO

AVAILABLE IN
ALU ANODIZED 13611 9200 ANO



 [View on website](#)



General info	
LOCATION	outdoor
INSTALLATION	Floor Recessed,Wall Recessed
CUTOUT SHAPE/SIZE (MM)	round - 41
RECESSED DEPTH (MM)	45
INGRESS PROTECTION	IP67
PROTECTION AGAINST MECHANICAL IMPACT	IK03
WEIGHT (KG)	0.1
ADJUSTABILITY	non adjustable
INFORMATION	EXCL.LED POWER SUPPLY 350mA-DC










Electrical info	
CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	E

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 1W / CRI>90 (R9: 55) / 2700K / 120lm
TM-30 VALUES	rf: 91 / Rg:100
SDCM	SDCM3
RISKGROUP	RG2
LM80	L90B10 > 150000
LED TECHNICS (LIGHT SOURCE)	120lm // 1W // 124lm/W
LED TECHNICS (LUMINAIRE)	35lm // 1W // 30lm/W

Requirements	
LED POWER SUPPLY 350mA-DC DIM	

For detailed installation instructions, please consult the manual : [13611_XXX0_HAND.pdf](#)











FINISH YOUR SPECIFICATION

LED power supplies			#
	300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1	3->14	☐
	300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	3->14	☐
	300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL	3->14	☐
	300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL	3->14	☐
	300 90 60 LED POWER SUPPLY MULTI-POWER DIM7	12 0 0	☐
	300 90 61 LED POWER SUPPLY MULTI-POWER DIM6	16	☐
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	26(25)	☐
	300 90 64 LED POWER SUPPLY MULTI-POWER DIM7	4->18(15)	☐
	300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	3->15	☐

DELTALIGHT

LEDS C R ST 927







13611 9200 ANO

	300 90 68	LED POWER SUPPLY MULTI-POWER DIM5	2->17(15) ☐
	300 90 69	LED POWER SUPPLY MULTI-POWER HV DIM9	8->40(39) ☐
	300 90 91	LED POWER SUPPLY 350mA-DC / 15W	14(10) ☐
	300 90 104	LED POWER SUPPLY 350mA-DC / 6W	4 ☐
	300 90 112	LED POWER SUPPLY 350mA-DC / 18W	15 ☐
	300 90 124	LED POWER SUPPLY MULTI-POWER DIM7	6->17(15) ☐
	300 90 125	LED POWER SUPPLY MULTI-POWER MINI DIM5	4->17(15) ☐
	300 90 135	LED POWER SUPPLY MULTI-POWER HV	17->29 ☐
	21012 0010	LED POWER SUPPLY MULTI POWER	6->15 ☐
	21012 0021	LED POWER SUPPLY MULTI POWER DIM1	4->19 ☐

DELTALIGHT

LEDS C R ST 927

13611 9200 ANO

	21012 0035	LED POWER SUPPLY MULTI POWER DIM5	4->19 ☐
	21012 004W	LED POWER SUPPLY MULTI-POWER WDL	25(25) ☐
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	4->19 ☐
	21012 0258	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	7->10 ☐
	21012 0268	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	10->15 ☐
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	3->15 ☐
	21012 0308	LED POWER SUPPLY 350mA / 7,35W DIM8	5->7 ☐
	21012 0480	LED POWER SUPPLY 350mA-DC / 17W IP68	2->17(15) ☐
	21032 0295	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	3->14 ☐

DELTALIGHT

LEDS C R ST 927

13611 9200 ANO

Notes: